

ELECTRICAL CONTINUITY DECLARATION

Producer:	VERGOKAN NV
Reportname:	INOXKBSI 60*---*---
Product description:	Cable tray with interlocking ends 60
Devices under test : (Product references)	INOXKBSI 60*075*0.80 INOXKBSI 60*600*1.00 INOXVM 6*10
Test according to:	§ 11.1.2 of the IEC 61537
Description of testmethode:	A current of 25 A ± 1A A.C. having a frequency of 50 Hz to 60 Hz supplied by a source with a no-load voltage not exceeding 12 V shall be passed through the length of the samples. The voltage drop shall be measured between two points 50 mm each side of the coupler or integral coupling and again between two points 500 mm apart on one side of the joint. The impedances shall not exceed 50 mΩ across the joint and 5 mΩ per meter without the joint.
Manufactured by:	VERGOKAN N.V.
Test device:	HYAMP III 3130
Calibration certificate number:	130624-3130_9352036

[Declaration] :

We declare that above mentioned products are tested by VERGOKAN according to § 11.1.2 of the IEC 61537.



DESCRIPTION OF TEST:

Test number	Setup	Measuring points	Criteria to pass the test
1	Two cable trays INOXKBSI 60*075*0.80 coupled with INOXVM 6*10	On both trays 50mm of the coupling.	Impedance can not exceed 50mΩ
2	Two cable trays INOXKBSI 60*600*1.00 coupled with INOXVM 6*10	On both tray's 50mm of the coupling.	Impedance can not exceed 50mΩ
3	INOXKBSI 60*075*0.80	On the tray, 500mm apart from each other	Impedance can not exceed 5mΩ/m
4	INOXKBSI 60*600*1.00	On the tray, 500mm apart from each other	Impedance can not exceed 5mΩ/m

RESULTS OF TEST:

Test number	Test	Impedance	Result
1	1	5 mΩ	Pass
	2	5 mΩ	Pass
	3	6 mΩ	Pass
2	1	4 mΩ	Pass
	2	4 mΩ	Pass
	3	5 mΩ	Pass
3	1	5 mΩ	Pass
	2	5 mΩ	Pass
	3	5 mΩ	Pass
4	1	4 mΩ	Pass
	2	5 mΩ	Pass
	3	5 mΩ	Pass

CONCLUSION:

All the devices under test where tested as described above and did meet their criteria to pass the test.

We can state that the cable tray INOXKBSI 60*---*--- is conform to § 11.1.2 of the IEC 61537.



Thomas Leus
Operations Director

Oudenaarde, 12/11/2013

* Pictures of the test setup canbe obtainedon request

On condition that the product(s) is/are used in the manner intended and/or in accordance with the current installation standards and/or with the manufacturer's recommendations.